

## RA-4961-K1Q Wireless Receiver and Wireless Pushbutton

The RA-4961-K1Q Wireless Alert System can be synced with a wide variety of wireless devices to suit almost any situation.

### Kit Includes:

- Wireless Receiver (RA-4961Q) and Wireless Pushbutton (RA-4961-PBQ)

### Features:

- Up to 1,000ft (305m) transmission range\*
- 18 programmable ringtones
- Connect up to 4 wireless transmitter accessories
- Audible and visual alert via built-in speaker and flashing light
- Wall or desktop mountable
- Output terminals for optional auxiliary device
- Each channel independently programmable

### Specifications:

<b>Model Number</b>	<b>RA-4961Q</b>
<b>Frequency</b>	914.8MHz
<b>Channels</b>	4
<b>Accessories per channel</b>	1
<b>Relay output (Channel 4 only)</b>	1(Form C Relay), 1A@50VDC
<b>Power Supply</b>	3 "C" batteries or 6VDC power adapter (Both not included)
<b>Estimated battery life</b>	270 days (3 triggers/day)
<b>Receiver low battery indicator</b>	Notification LED flashes every 5 seconds
<b>Accessory low battery</b>	Zone LED for accessory blinks continuously
<b>Sound level (dB)</b>	Up to 96dB@1ft(30cm)
<b>Operating Temperature</b>	32°~140°F (0°~60°C)
<b>Dimensions</b>	5 <sup>1</sup> / <sub>4</sub> "x1 <sup>9</sup> / <sub>16</sub> "x6 <sup>5</sup> / <sub>8</sub> " (133x40x169mm)

<b>Model Number</b>	<b>RA-4961-PBQ</b>
<b>Frequency</b>	914.8MHz
<b>Transmission range*</b>	Up to 1,000ft (305m)
<b>Channels</b>	1
<b>Power supply</b>	CR2032 Battery (included)
<b>Estimated battery life</b>	400 days (3 triggers/day)
<b>Low battery indicator</b>	Zone LED on receiver blinks continuously
<b>IP rating</b>	IP45
<b>Operating Temperature</b>	-4°~140°F (-20°~60°C)
<b>Dimensions</b>	1 <sup>5</sup> / <sub>16</sub> "x1 <sup>1</sup> / <sub>16</sub> "x3 <sup>7</sup> / <sub>16</sub> " (34x18x87mm)



RA-4961Q



RA-4961-PBQ

\*Line of sight. Transmission range will vary depending on installation and operating environment.

### SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: [www.seco-larm.com](http://www.seco-larm.com) Email: [sales@seco-larm.com](mailto:sales@seco-larm.com)

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®

PI\_RA-4961-K1Q\_151210.docx

Copyright 2015 © SECO-LARM U.S.A., Inc. All rights reserved.  
All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.  
The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

